Как обновить прошивку на камере VStarcam



Подсоедините с помощью сетевого кабеля камеру к компьютеру или роутеру, подключите камеру к сети питания,



Скачайте и запустите на компьютере программу Smart Uprade Tool,



Нажмите кнопку "Search LAN IP Camera",

n1.1	A CONTRACTOR
on 1. 1, Upgrade system rom automatically J.Notice: Upgrading is risky, if having son	y by using this tool.Systen nething unclear,please co
" button, select the current LAN or omplete the new firmware version admin, password is 8888888, as an	nline IP camera or dir of the lookup and up nended, please upgra
amera	Upgrade
Port: 81	Account
	n1.1 n1.1, Upgrade system rom automatically Notice: Upgrading is risky, if having son "button, select the current LAN or omplete the new firmware version admin, password is 888888, as an amera Port: 81

кнопку "**ОК**",

В открывшемся окне выберите камеру для обновления и нажмите



Нажмите кнопку "Upgrade Firmware" и ожидайте окончания процесса прошивки.

Search LAN IP camera			Upgrade Firr	nware
IP address 192.168.0.16	Port:	81	Account:	admin
Operation Log				
26.11.2013 21:23:47:Device connected in 26.11.2013 21:23:48:The version of presi 26.11.2013 21:23:48:The version of lates 26.11.2013 21:23:48:Downloading rom fo 26.11.2013 21:23:51:Begin to upgrade de 26.11.2013 21:23:54:Successfully upgrade 26.11.2013 21:25:23:IP Cam is Working! 26.11.2013 21:25:24:Device connected in 26.11.2013 21:25:25:The version of presi 26.11.2013 21:25:25:The version of lates 26.11.2013 21:25:25:Downloading rom fo 26.11.2013 21:25:29:Begin to upgrade de 26.11.2013 21:25:32:Successfully upgrade 26.11.2013 21:25:32:Successfully upgrade 26.11.2013 21:25:32:Successfully upgrade 26.11.2013 21:25:32:Successfully upgrade	ent device re it device ro r upgrading evice"s rom e ROM, it is ormally ent device it device ro r upgrading evice"s rom e ROM, it is	rom is :48. om is :48.2 g n, please ho s going to ro rom is :TH2. g n, please ho s going to ro	2.64.195 .64.203 Id the connection of eboot the device, ple 2.0.1.23 .0.1.25 Id the connection of eboot the device, ple	the device norma ase wait the device norma



После обновления рекомендуется сбросить установки устройства к заводским.